### lucent<sub>®</sub>




#### ProSpex Duo Accent Part L Compliant Downlight


тм65.2	11kgCO2e
TM66	2.3 CEAM



108mm (4.25") overall diameter. 360° rotation. Up to 35° tilt. Available with standard trim kit or plaster-in kit for flush appearance. Family of matching products also available. Required depth height + 25mm^



31603-LED + 3000-PBZ Cut-out Ø101mm (Ø3.97")



31603-LED + 3000-PCZ Cut-out Ø96mm (Ø3.78")

LED Source	LED51/Q-HO	LED51/Q-HO	LED51/3-HO	LED51/Q-HO	1
CCT	3000K	3000K	3000K	3000K	≥75 Dwellings
Drive Current	350mA	350mA	350mA	350mA	Compliant
Power inc Driver	14.0W	14.0W	14.0W	14.0W	
Beam Angle	NF (17°)	MF (24°)	FL(32°)	WFL (51°)	17
Delivered Lumens	1775	1710	1770	1770	≥95 General Compliant
Delivered Intensisty cd	1384	8166	5784	2604	
Delivered Lumens per circuit watt	127	122	126	126	
Forward Volt	34V	34V	34V	34V	
CRI	≥93 CRI	≥93 CRI	≥93 CRI	≥93 CRI	≥80 Display Compliant


Lumen output for other CCTs use the following multification factors to the 3000K figures above: 2700K x 0.98. 4000K x 1.02

# lucent<sub>®</sub>

Project Ref:			Location Ref:				
Fixture Ord	er Code: [	31603-LED –					
	l						
Fixture – 31603-LED –	Duo Accent wi	ith LED51					
WH BK RAL ABR1 ABZ1 PCH1 PNK1 PBR1	White Black Custom RAL F Antique Brass Antique Bronz Polished Chro Polished Nicke Polished Brass	Brass Bronze Chrome Nickel					
IP Rating – 54	IP54						
Installation Installation 3000-PBZ 3000-PCZ Module Ord	 Trim Plast	kit for trimmed appearance er-kit for seamless flush appea	rance				
LED – LED51/3-HO	LED50 ONE G	QUANTUM HE High Output					
CCT – 27 30 40	2700K 3000K 4000K***						
Beam – NF MF FL WFL	Narrow Flood Medium Flood Flood Wide Flood						
***contact Luce	nt for availabilit	у					
Driver Opti Protocol – S A P D B	ONS: Non-Dim Analogue (0-10 Phase DALI Bluetooth**	] ])v)	Emergency Options: Emergency E Maintained 3hr Emergency ED Maintained 3hr DALI Self Test ES Maintained 3hr Self Test				

## lucent

#### **Finish selection**



# lucent

#### **Technical Details**

\*Custom RAL code must be specified. Custom RAL colours can increase prices and lead times

Dimming. Whilst Lucent can offer the majority of its luminaires with various dimming options, it remains the responsibility of the specifier/installer to check and ensure compatibility of any control equipment used. Additional cabling may be required depending on the dimming protocol specified.

\*\*Bluetooth (wireless) is the communication method. The exact dimming protocol must be confirmed to allow the selection of suitable drivers or bluetooth devices.

^ Depth indicated is the minimum recess depth for the luminaire with a remote mounted LED driver. Installing a driver through either the luminaire cut-out or installation kit may require additional recess depth, please refer to the relevant luminaire installation instructions for further details.Data correct at time of publishing

First Fix Requirement. Luminaire comprised of fixture body with ceiling trim and installation kit, which is to be fitted into the ceiling once finished. Ensure correct alignment of the installation kit before final assembly (see luminaire instllation instructions for details)

IP Rating. Tested from underside of the ceiling

Note that the picture of the finishes provided is for illustrative purposes only. The finishes may vary in colour, texture and appearance. Contact Lucent lighting Ltd for more information.

It is the policy of Lucent Lighting to continually review and improve its products and therefore reserve the right to change any details of product or withdraw specifications without prior notice.

Luminaires designed to comply with EN60598 and all other standards.

This specification sheet supersededs all previous versions.

All intellectual property rights pertaining to the product described above and to this document are owned by or licensed to Lucent Lighting Ltd.

We reserve the right to take whatever action is necessary to protect those intellectual property rights.