

## Edge4.25 Trimless Triple



108mm (4.25") overall diameter. Edge baffle to ensure aperture is glare free and for a professional look. Supplied with mud-in kit for flush appearance. Family of matching products also available. Required depth height + 25mm^



A31413-F-LED + 3000-PCZ Cut-out 98mm (3.85") Ø



A31413-A-LED + 3000-PCZ Cut-out 98mm (3.85") Ø



### Fixture Output Data

#### LED51/2

LED Source	LED51/2	LED51/2	LED51/2	LED51/2
CCT	3000K	3000K	3000K	3000K
Drive Current	350mA	350mA	350mA	350mA
Power inc Driver	13.6W	13.6W	13.6W	13.6W
Beam Angle	12°	24°	38°	60°
Delivered Lumens	759	847	997	931
Delivered Intensisty cd	10273	4613	2877	1273
Efficacy Im/w	56	62	73	69
Forward Volt	33V	33V	33V	33V
CRI	≥90 CRI	≥90 CRI	≥90 CRI	≥90 CRI

.....

#### LED51/U

LED Source	LED51/2	LED51/2	LED51/2	LED51/2
CCT	3000K	3000K	3000K	3000K
Drive Current	350mA	350mA	350mA	350mA
Power inc Driver	13.6W	13.6W	13.6W	13.6W
Beam Angle	12°	24°	38°	60°
Delivered Lumens	726	717	855	799
Delivered Intensisty cd	10777	4080	2047	1041
Efficacy Im/w	53	53	63	59
Forward Volt	33V	33V	33V	33V
CRI	≥98 CRI	≥98 CRI	≥98 CRI	≥98 CRI

### LED51SS

LED Source	LED51SS
CCT	3000K
Drive Current	500mA
Power inc Driver	6.75W
Beam Angle	7°
Delivered Lumens	456
Delivered Intensisty cd	18626
Efficacy Im/w	68
Forward Volt	11.5V
CRI	≥90 CRI

Above data is for singular fixture



#### LED51WD

LED Source	LED51WD	LED51WD
CCT	3000K	3000K
Drive Current	500mA	500mA
Power inc Driver	17.1W	17.1W
Beam Angle	28°	39°
Delivered Lumens	596	688
Delivered Intensisty cd	2081	1347
Efficacy Im/w	35	40
Forward Volt	29.1V	29.1V
CRI	≥95 CRI	≥95 CRI
Test results at full output		

.....

#### LED51TW

LED Source	LED51TW	LED51TW
CCT range 5000K-2000K	@ 3000K	@3000K
Drive Current (max per channel)	700mA	700mA
Power inc Driver Max	15.1W	15.1W
Beam Angle	25°	35°
Delivered Lumens	551	629
Delivered Intensisty cd	2290	1339
Efficacy Im/w	37	42
Forward Volt (max per channel)	18.4V	18.4V
CRI	≥95 CRI	≥95 CRI



	Location Ref:
rder Code:	
Edge4.25 Fixed with LED51 Edge4.25 Accent with LED51	
White (RAL 9010) Black (RAL 9005) Custom RAL Colour*	
Damp Wet Standard Location	
kness 1/2" 5/8" 3/4" Custom	
n Order Code: 3000-PCZ  Mud-kit for seamless flush appearance	
	Edge4.25 Fixed with LED51 Edge4.25 Accent with LED51  White (RAL 9010) Black (RAL 9005) Custom RAL Colour*  Damp Wet Standard Location  aness 1/2" 5/8" 3/4" Custom  Order Code: 3000-PCZ




Project Ref:		Location Ref:
LED Order	Code:	-
LED — LED51/2 LED51/U LED51SS LED51WD LED51TW	LED50 ONE GEN2 (90 CRI) LED50 ONE ULTRA (98 CRI) LED50 ONE SuperSpot (90 CRI) LED50 ONE Ambiance WarmDim (95 CRI) LED50 ONE Tuneable White (95 CRI)	
CCT -		
LED51/2 CCT 27 30 35 40	2700K 3000K 3500K 4000K	
LED51/U CCT 27 30 35	2700K 3000K 3500K	
LED51SS CCT 27 30 35 40	2700K 3000K 3500K 4000K	
LED51WD CC 2720 3020	2T 2700K - 2000K 3000K - 2000K	
LED51TW CC 5020	T 5000K - 2000K	
Beam -		
LED51/2 Bean 12 24 38 60	n 12° 24° 38° 60°	
LED51/U Bear 12 24 38 60	n 12° 24° 38° 60°	
LED51SS Bear	n 7°	
LED51WD Bea 28 39	am 28° 39°	
LED51TW Bea 25 35	um 25° 35°	

CCT - Please choose CCT depending on LED50 ONE Module required

Beam - Please choose Beam Angle depending on LED50 ONE Module required

# lucent<sub>®</sub>







Frosted Lens (LLFR)

Solite/Diffusing Lens (LLDF)





Warm Tone (LLCC)

**Heavy Spread Lens (LLHS)** 

**Linear Spread Lens (LLLS)** 

Accessories Order Code:

Louvre/Lens

LL45 Honeycomb Louvre
LLCC Warm Tone Lens
LLUV UV Lens
LLDF Solite/Diffusing Lens

LLFR Frosted Lens LLLS Linear Spread Lens

LLS Linear Spread Lens LHS Heavy Spread Lens

#### Technical Details

\*Custom RAL code must be specified. Custom RAL colours can increase prices and lead times

Dimming. Whilst Lucent can offer the majority of its luminaires with various dimming options, it remains the responsibility of the specifier/installer to check and ensure compatibility of any control equipment used. Additional cabling may be required depending on the dimming protocol specified.

- \*\*DALI Type 6 requires two DALI addresses, one for CCT control the other for Intesisty control. DALI Type 8 is a single DALI Type 8 address for CCT and Intesisty control. Please check which control system is being used before specifying.
- \*\*Bluetooth (wireless) is the communication method. The exact dimming protocol must be confirmed to allow the selection of suitable drivers or bluetooth devices.
- ^ Depth indicated is the minimum recess depth for the luminaire with a remote mounted LED driver. Installing a driver through either the luminaire cut-out or installation kit may require additional recess depth, please refer to the relevant luminaire installation instructions for further details. Data correct at time of publishing

First Fix Requirement. Luminaire comprised of fixture body with ceiling trim and installation kit, which is to be fitted into the ceiling once finished. Ensure correct alignment of the installation kit before final assembly (see luminaire instillation instructions for details)

Location. Tested from underside of the ceiling

It is the policy of Lucent Lighting to continually review and improve its products and therefore reserve the right to change any details of product or withdraw specifications without prior notice.

This specification sheet supersededs all previous versions.

All intellectual property rights pertaining to the product described above and to this document are owned by or licensed to Lucent Lighting Ltd.


We reserve the right to take whatever action is necessary to protect those intellectual property rights.

Please notify Lucent Lighting Ltd of any inaccuracies immediately. E&OE





Project Ref:\_\_\_\_\_\_ Location Ref:\_\_\_\_\_




O.C."	L	LI	W	WI
10.00"	30.60"	35.15"	12.00"	14.45"
(254mm)	(778mm)	(893mm)	(305mm)	(369mm)

LMT-M3-NIC


Tray Order	Code: [LMT-M3-NIC] -	- LED51 -	
Housing Type LMT-M3-NIC  Mounting Ha 09 14 36 BB CB LED LED51	Lucent Triple Mounting Tray Non-Insulated Ceiling		
Supply Voltag 120 277	ge		
Protocol —— S P LP ESS LHE LAE A ED EA B	Non-Dimmable TRIAC/Phase (120V ONLY) Lutron Forward Phase 2-Wire (120V ONLY) EcoSystem 5-Series 5% EcoSystem Hi-Lume 1% Fade to Black Lutron 3-Wire Hi-Lume 1% Analog (0-10V) EldoLED DALI (Not Available for LED51WD) EldoLED Analog (0-10V) (Not Available for LED Bluetooth	A2 D6 D8 L	OL FOR LED51TW  Analogue (0-10V) 2-Channel DALI Type 6** DALI Type 8** Lutron (Consult Factory)
Emergency E ES	Maintained 3hr Emergency Maintained 3hr Self Test		



Project Ref:\_\_\_\_\_ Location Ref:\_\_\_\_




LH-M3-6.75





Project Ref:\_\_\_\_\_ Location Ref:\_\_\_\_



LH-M3-8.50

